



# VOSKER V100

## 4G Wireless Outdoor Security Camera



## No Wi-Fi? No problem.

Ideal for a construction site, farm, country house, vacation home, rental property, parking lot or marina. Monitor anything, anywhere! No need for Wi-Fi thanks to 4G based mobile connectivity to transmit photos to your phone and get mobile alerts.



Works without Wi-Fi thanks to 4G connectivity



Weather-Resistant and rugged design



Monitor job site, farm, cabin or any other remote locations



Night vision and automatic motion detection



Day and night photos with custom alerts on the mobile app



Rechargeable battery pack, 8 AA batteries or 12V



Preactivated SIM card, SD card and mount included



FREE mobile security plan offered



Local photo-video backup on SD card



VOSKER two (2) year limited warranty.



# VOSKER®

For more information or to buy an international model, contact [support@vosker.com](mailto:support@vosker.com)



## GENERAL SPECIFICATIONS - V100

### PHOTO

<b>Photo Resolution</b>	Full HD 1920×1080 on SD card and 600×338 on mobile app
<b>File Format</b>	JPG
<b>Time Lapse Mode</b>	Customizable preset intervals
<b>Multi Photo Mode</b>	Up to 2 photos per detection
<b>Information Stamped on Photos</b>	Date, time and temperature (°C/°F)
<b>Operation Mode</b>	Photo, video, time lapse or photo and time lapse
<b>Capture Mode</b>	Colored photos by day and black and white by night (with IR) – White IR LED with smoke glass window (super low glow)
<b>Night Vision (IR setting)</b>	Blur reduction, boost, and optimal
<b>Optical Field of View</b>	43.6°

### VIDEO

<b>Video Access</b>	SD card only
<b>Video Resolution</b>	1080p, 10 fps
<b>Video File Format</b>	AVI
<b>Video Length</b>	10 s, 30 s, 60 s, and 90 s
<b>Photo First</b>	Takes a picture before recording. Make sure to enable PHOTO FIRST option in the mobile app to allow the camera to send a photo to your phone for every video recorded.
<b>Capture Mode</b>	Color by day and black and white by night (with IR)
<b>Audio Recording</b>	N/A on this model



## GENERAL SPECIFICATIONS - V100

### MEMORY

Capacity	External memory: SD/SDHC card up to 32 GB (8 GB card included)
----------	--

### BATTERY / POWER SOURCE

Lithium or Standard Batteries	8 × AA (not included) or lithium battery pack V-LIT-B (not included) required to operate the camera
12V Power Jack	12V battery (V-CASE-12V) or 12V adaptor (V-AT12V)

### DETECTION SYSTEM

Detection System	PIR
Detection Angle	50°
Motion Sensor	1 sensor for a total of 5 detection zones
Detection Range	100 ft
Optional Delay Between Detections	Preset delays of 10 s, 1 min, 3 min, 5 min, 10 min, 15 min and 30 min
Trigger Time	0.03 s

### NIGHT VISION / FLASH

LED	42 LED (45°)
Type	White LED super low glow
Flash Range	90 ft
Exposition	Automatic adjustment of infrared light strength



## GENERAL SPECIFICATIONS - V100

### DIMENSIONS

Camera Body	4.4" W × 3.3" D × 5.2" H
-------------	--------------------------

### CELLULAR

SIM Card	Included
Mobile Connectivity	4G
Reception	Mobile app or web app
Required Carrier	No specific carrier
Synchronisation Frequency	1/day, 2/day, 6/day, 12/day or each detection
GPS Localisation System	N/A on this model
Camera Configuration	Mobile app or web app
Trial Period	30 days unlimited photos to test all the features. Free plan offered.

### GENERAL CONFIGURATION

Language	English, French, Spanish, and German
Sensitivity Settings	Low, normal and high
Date Format	mm/dd/yyyy or dd/mm/yyyy
Photo Stamp Information	Yes, when enabled
Temperate Units	°C or °F
Information in "About" Menu	S/W, H/W, model, device name, IMEI, SIM, region, and modem version
Schedule Set Up	Complete control over schedule
Time Format	12H or 24H



## GENERAL SPECIFICATIONS - V100

### OTHER

<b>External Antenna</b>	Included
<b>External Extra Long Antenna</b>	Sold separately
<b>Mounting Bracket</b>	Adjustable mounting arm and strap included
<b>Operating Temperature Range</b>	40°C to -40°C
<b>Certifications</b>	FCC, CE, IP65 Weather-resistant
<b>Warranty</b>	<a href="http://www.vosker.com/warranty-and-repair/">www.vosker.com/warranty-and-repair/</a>